



| | |
|--|---|
| Markings & Standard(s) | CE, UKCA, BS EN 60669-2-1 |
| Operating Voltage | 220-240V AC |
| Main Frequency | 50Hz |
| Minimum Load | N/A |
| Maximum Load | 1000W |
| Switch Type | Three Way (Intermediate) |
| Dimming Protocol | N/A |
| Mounting Box Depth (Min) | 25mm |
| Terminal Capacity | 1 x 4mm ² / 1 x 2.5mm ² / 3 x 1.5mm ² / 4 x 1mm ² |
| Terminal Markings | L1, L2, L1, L2 |
| Neutral Required | No |
| Short Circuit Protection | N/A |
| Overload/Overcurrent Protection | N/A |
| Thermal Protection | N/A |
| Soft Start | N/A |
| Power Failure | N/A |
| Memory | N/A |
| Min/Max Level Setting | N/A |
| Driving Mode | N/A |
| Product Dimensions | 60mm x 40.5mm x 25mm |
| Climate Range | 0°C to 40°C, Humidity 0% to 95% non-condensing |
| Recommended Location | Indoor use only |
| Maximum Installation Altitude | 2000m |
| IP Rating | IP2XD |
| Trademarks | Enkin is a registered trademark number: UK00003707694, Date: 07 May 2021 |



| | |
|------------------------------------|-----------------|
| Operating Voltage | 240V ac |
| Nominal Operating Frequency | 50 Hz |
| Dimming Technique | N/A |
| Compliance | BS EN 60669-2-1 |



| Load Symbol | Compatible Loads | Max Loads |
|-------------|---|-----------|
| | LED lighting | 1000W |
| | 240V Incandescent & Halogen lamps | 1000W |
| | Low voltage lighting with electronic transformers | 1000W |

ON & OFF FUNCTION

Dummy dimmer switch is activated by pressing the dimmer shaft.

WIRING EXAMPLE

