

122363

## Saxby LinX65 CCT 5FT Emergency

### FEATURES

- 5 years (2 years + 3 years) extended warranty
- Frosted & grey PC finish
- Constructed from polycarbonate
- IP65
- IK08
- Plenty of space in the base for quick installation & wiring
- Lift & lock spring clips
- Multiple pop-out M20 knockouts on both ends, sides & back
- Multiple fixing points for push connector
- Removable push connector can face either end for easy wiring
- Built-in loop in/out cable restraints
- Click on MW, EM, DALI, 0-10V, Casambi accessories
- MW is 3-i-1: on/ff, corridor, photocell
- EM kit accessory is 2-in-1: manual test & self test
- Safety rope included
- BESA compatible
- Testing holes on the connector for Continuity and IR tests (Using GS38 probes)
- 3 hours emergency maintained & non-maintained fitting

### SPEC DATA

Product Wattage:	26W/34W/43W/50W
Product Lumen:	3900/5100/6450/7500
Lumen/W:	150
EM Wattage:	2W
EM Lumen:	300Lm
Kelvin:	3000/4000/6000K
Energy Rating:	D
Beam Angle:	120°
SDCM:	≤ 6
CRI:	≥ 80
Lifetime (Hours):	50000
Power Factor:	> 0.9
LED Brand:	BMTC
Driver Type:	Constant Current 360mA
Inrush Current at Start Up:	15A
Driver Output Voltage:	110-165V DC
Product Voltage:	220-240V
Hertz:	50/60
Surge Protection (KV):	1
Operating Temp.:	-20 to 45 Degree
Battery:	LiFePO4 6.4V 1800mAh
Product Weight (KG):	2.05
Terminal Block:	4-way fast fix
Class:	1

### ACCESSORIES

- 122321, Saxby X-Series Sensor MW & Photocell
- 124291, Saxby X-Series DALI Driver
- 124292, Saxby X-Series 0-10V Driver
- 124293, Saxby X-Series Casambi Driver

